

## HIGH PRESSURE SODIUM

WATT	STARTING AMPS	RUNNING AMPS	POWER FACTOR CORRECTION CAPACITOR
70	0.72	0.45	10 $\mu$ F
150	1.30	0.88	20 $\mu$ F
250	2.10	1.42	30 $\mu$ F
400	3.80	2.20	45 $\mu$ F
1000	8.80	5.50	100 $\mu$ F

## METAL HALIDE

WATT	STARTING AMPS	RUNNING AMPS	POWER FACTOR CORRECTION CAPACITOR
70	0.72	0.45	10 $\mu$ F
100	1.00	0.75	12 $\mu$ F
150	1.70	0.82	20 $\mu$ F
250	2.80	1.42	30 $\mu$ F
400	3.80	2.20	45 $\mu$ F
1000	9.60	5.20	90 $\mu$ F
2000 8.8A (380V)	7.20	5.90	37 $\mu$ F
2000 10.3A (380V)	8.20	6.80	60 $\mu$ F

## MERCURY VAPOUR

WATT	STARTING AMPS	RUNNING AMPS	POWER FACTOR CORRECTION CAPACITOR
80	0.90	0.45	10 $\mu$ F
125	1.35	0.68	10 $\mu$ F
250	2.60	1.35	15 $\mu$ F
400	4.20	2.10	20 $\mu$ F

## COMPACT FLUORESCENTS

WATT	CORRECTED LINE CURRENT	POWER FACTOR CORRECTION CAPACITOR
1 X PL 9	0.06 A	2 $\mu$ F
2 X PL 9	0.12 A	4 $\mu$ F
1 X PL 13	0.08 A	2 $\mu$ F
2 X PL 13	0.16 A	4 $\mu$ F
1 X PL 18	0.11 A	2 $\mu$ F
2 X PL 18	0.22 A	4 $\mu$ F
1 X PL 26	0.15 A	3 $\mu$ F
2 X PL 26	0.30 A	6 $\mu$ F
1 X 16W 2D	0.10 A	2 $\mu$ F
1 X 28W 2D	0.16 A	3 $\mu$ F

## FLUORESCENTS

WATT	STARTING AMPS	RUNNING AMPS	POWER FACTOR CORRECTION CAPACITOR
1 x 18	0.17	0.13	4 $\mu$ F
2 x 18	0.29	0.22	4 $\mu$ F
1 x 36	0.29	0.22	4 $\mu$ F
2 x 36	0.58	0.44	8 $\mu$ F
1 x 58	0.42	0.32	6 $\mu$ F
2 x 58	0.84	0.64	12 $\mu$ F